

**DS-PR1-WE**

The wireless repeater, supporting 868 Mhz wireless communication, Tri-X and Cam-X wireless protocol, multiple enrollment methods, two-way wireless communication, and auto-pairing, is used for extending RF distance in alarm system.

- 868MHz two-way wireless communication
- Two-way communication, stable and secure
- LED display, show the different feedbacks with easy understanding
- Up to 35 hrs battery backup after mains lost, no worry about communication
- Finding and connecting up to 8 PIRCAM or smoke detectors automatically, smart auto-pairing
- Easy installation with new designed structure



## ▪ Specification

Model		DS-PR1-WE
Software features	Tamper-Proof	1, Front and Back
	Auto Paring	Supported
	PIRCAM Paring	Supported
Hardware features	Serial port	2, for debug
	Power Switch	1
RF transmission	RF method	Two way communication
	RF Modulation	2GFSK
	RF Frequency	868MHz
	RF Distance	1600m (Open area)
	Wireless Security	AES-128
Electrical characteristics	Power supply	100VAC ~ 240VAC
	Battery type	Built in Battery Li
	Battery life span	Up to 35 hours
Display	LEDs Status	3, Register/Signal (Green/Red), Power (Green), Fault (Amber)
General	Operation temperature	- 10°C ~ 55°C
	Operation humidity	10% ~90%
	Shell material	Plastic
	Dimension(Wx HxD)	150*150*25mm
	Weight	372g
	Color	White
	Installation method	Wall Mounting

## ▪ Available Model

DS-PR1-WE

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Australia**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision Canada**  
T +1-866-200-6690  
sales.canada@hikvision.com

**Hikvision Thailand**  
T +662-275-9949  
sales.thailand@hikvision.com

**Hikvision Europe**  
T +31-23-5542770  
sales.eu@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
info.it@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com

**Hikvision Turkey**  
T +90 (216)521 7070- 7074  
sales.tr@hikvision.com

**Hikvision Malaysia**  
T +601-7652-2413  
sales.my@hikvision.com

**Hikvision UK & Ireland**  
T +01628-902140  
sales.uk@hikvision.com

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Kazakhstan**  
T +7-727-9730667  
nikia.panfilov@hikvision.ru

**Hikvision Vietnam**  
T +84-974270888  
sales.vt@hikvision.com

**Hikvision UAE**  
T +971-4-4432090  
salesme@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Tashkent**  
T +99-87-1238-9438  
uzb@hikvision.ru

**Hikvision Hong Kong**  
T +852-2151-1761  
info.hk@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Korea**  
T +82-(0)31-731-8817  
sales.korea@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
info.pl@hikvision.com

**Hikvision Indonesia**  
T +62-21-2933759  
Sales.Indonesia@hikvision.com

**Hikvision Colombia**  
sales.colombia@hikvision.com